

TIGER



TX1-A

TX2-A

Tiger transmitter TX1-A/TX2-A	
Article number:	TX1-A; TG-T3-4-0000 TX2-A; TG-T3-5-0000
Application areas:	Cranes, EOT cranes, hoists, towing and recovery vehicles, crusher, dump bodies, load changers, agriculture machines a.o.
Duplex:	Yes
Display:	TX1-A; Yes TX2-A; No
Frequency:	433 - 434 MHz (69 channels)
Mod. Type:	Narrow band FM-modulation
Coding:	Digital pulse code
Code comb.:	4,2 billion (factory coded)
Functions:	TX1-A; 10 x 2 TX2-A; 12 x 2
Stop function:	Approved according to SIL3 IEC 61508
Radio type:	Low IF topology
Output:	10m W (50 ohm)
Antenna:	Built-in
Power supply:	Exchangable rechargeable battery (Li-ion)
Operating time:	Apr. 30 hrs. continuous use
Power consumption:	TX1-A; apr. 50-250 mA TX2-A; apr. 50 mA
Weight:	Apr. 300 g (0,66 lb)
Dimensions:	210 x 80 x 40 mm (8.27 x 3.15 x 1.57 in)
Protection:	IP 65
Recommended receiver:	All Tiger receivers

TELE RADIO AB
Sweden, Main office
Tel. +46 (0)31-748 54 60
e-mail: info@tele-radio.com

www.tele-radio.com

TELE RADIO SVERIGE
Sweden
Tel. +46 (0)31-724 98 00
e-mail: sverige@tele-radio.com

TELE RADIO OÜ
Estonia
Tel. +372 44 511 55
e-mail: eesti@tele-radio.com

TELE RADIO GmbH
Germany
Tel. +49 (0)94 51-944 8 550
e-mail: deutschland@tele-radio.com

TELE RADIO ASIA
China
Tel. +86-(0)592-3111168
e-mail: china@tele-radio.com

TELE RADIO TURKEY
Turkey
Tel. +90 216 574 22 94
e-mail: turkiye@tele-radio.com

TELE RADIO LTD
England
Tel. +44 (0) 1625 509125
e-mail: england@tele-radio.com

TELE RADIO LLC
North America & Latin America
Tel. +1 (305) 459 0763
e-mail: america@tele-radio.com

TELE RADIO BV
Benelux
Tel. +31-(0)70-419 41 20
e-mail: benelux@tele-radio.com

TELE RADIO AS
Norway
Tel. +47-6933 4900
e-mail: norge@tele-radio.com

TIGER



JDx-A

Tiger joystick transmitter JDx-A	
Article number:	JD1-A: TG-T4-11-0000 JD2-A: TG-T4-5-0000
Application areas:	Cranes, EOT cranes, hoists, towing and recovery vehicles, crusher, dump bodies, load changers, agriculture machines a.o.
Duplex:	Yes
Display:	Yes
Frequency:	433 - 434 MHz (69 channels)
Mod. Type:	Narrow band FM-modulation
Coding:	Digital pulse code
Code comb.:	4,2 billion (factory coded)
Functions:	JD1-A: 2 joysticks with 2 speed JD2-A: 2 joysticks with 4 speeds
Radio type:	Low IF topology
Stop function:	Approved according to SIL3 IEC 61508
Output:	10m W (50 ohm)
Antenna:	Built-in
Power supply:	Exchangable rechargeable battery (Li-ion)
Operating time:	Apr. 15 hrs. continuous use
Power consumption:	Apr. 50-250 mA
Weight:	Apr. 1200 g (2.65 lb)
Dimensions:	210 x 130 x 40 mm (8.27 x 5.12 x 1.57 in)
Protection:	IP 65
Recommended receiver:	All receivers system Tiger



Vianet Sverige AB
Connecting Systems
Midgårdsvägen 20, S-973 34 LULEÅ
Tel: 0920-22 24 10, Fax: 0920-22 24 20
E-Mail: info@vianetab.se
Gsm: 070-545 14 52, 070-545 17 81

TELE RADIO AB
Sweden, Main office
Tel. +46 (0)31-748 54 60
e-mail: info@tele-radio.com

www.tele-radio.com

TELE RADIO SVERIGE
Sweden
Tel. +46 (0)31-724 98 00
e-mail: sverige@tele-radio.com

TELE RADIO OÜ
Estonia
Tel. +372 44 511 55
e-mail: eesti@tele-radio.com

TELE RADIO GmbH
Germany
Tel. +49 (0)94 51-944 8 550
e-mail: deutschland@tele-radio.com

TELE RADIO ASIA
China
Tel. +86-(0)592-3111168
e-mail: china@tele-radio.com

TELE RADIO TURKEY
Turkey
Tel. +90 216 574 22 94
e-mail: turkiye@tele-radio.com

TELE RADIO LTD
England
Tel. +44 (0) 1625 509125
e-mail: england@tele-radio.com

TELE RADIO LLC
North America & Latin America
Tel. +1 (305) 459 0763
e-mail: america@tele-radio.com

TELE RADIO BV
Benelux
Tel. +31-(0)70-419 41 20
e-mail: benelux@tele-radio.com

TELE RADIO AS
Norway
Tel. +47-6933 4900
e-mail: norge@tele-radio.com